

Push Dimm transformer - 230VAC - 12VDC

A power supply with an integrated dimmer, so it can be controlled with maintained units.



The power supply has standard 230V input and 12V DC output. With the built in dimmer you avoid having to connect a separate dimmer unit. It can dim from 0% to 100%.

It can be controlled with push-button and 150W also can handle 0-10V signal, 10V PWM and resistor / potentiometer.

Push-button / potentiometer is not included.

Buy online at:

www.matronics.eu/503380



3000mA - 36W

SKU 503379

Input voltage: 100-240VAC

Power factor: >0.85

Output voltage: 12VDC

Consumption: 36W

Current: 3A

Temperature: - 30°C ~ 65°C

Weight: 200

Dimensions: 30 x 175 x 44mm



6.250mA, 75W

SKU 503380

Input voltage: 100-240VAC

Power factor: >0.99

Output voltage: 12VDC

Consumption: 75W

Current: 6.2A

Temperature: - 30°C ~ 65°C

Weight: 500

Weight: 500

Dimensions: 30 x 293 x 43mm



12.500mA - 150W

SKU 503385

Input voltage: 100-240VAC

Power: >0.99

Output voltage: 12VDC

Current: 12.5A

Consumption: 150W

Weight: 580

Dimensions: 36 x 270 x 55mm

Product pictures

