

Dimmer switch, 12V-24V - 30 Amp.

Compact 12-24V DC dimmer with a rotary knob that can handle up to 30A.



DIP Switch 1-3 styrer PWM frekvensen			
1	2	3	PWM
0	0	0	500Hz
1	0	0	500Hz
0	1	0	750Hz
1	1	0	1kHz
0	0	1	3kHz
1	0	1	5kHz
0	1	1	10kHz

DIP Switch 4-5 styrer dempekurven		
4	5	Stigning på kurve
0	0	Standard
1	0	Driv start
0	1	Høj Start

Smart and compact 12-24V DC dimmer with built-in with a rotary knob that can handle up to 30A.

The dimmer is connected very simple, as there is only a single input and output channel. There are screw terminals for input and output.

The measurements of the box are 86x63x20mm (L x W x D) and the screw button is 16mm high.

Buy online at:

www.matronics.eu/500192

Specifications

Voltage	12V / 24V
Max power	360W
Max current 12V	30A
Max current 24V	15A



Dimmer switch, 12V-24V - 30 Amp.

SKU 500192

Dimensions: 20 x 65 x 85mm

Product pictures



DIP Switch 1-3 styrer PWM frekvensen			
1	2	3	PWM
0	0	0	300HZ
1	0	0	500HZ
0	1	0	700HZ
1	1	0	1KHZ
0	0	1	3KHZ
1	0	1	5KHZ
0	1	1	10KHZ

DIP Switch 4-5 styrer dæmpekurven		
4	5	Stigning på kurve
0	0	Standard
1	0	Svag start
0	1	Høj Start